

Power Supply & Consumption
Input Voltage
AC 110V~240V
Frequency
~50/60Hz
Phase
AC INPUT
Power Consumption (Sound Bar)
30W
Power Consumption (Subwoofer)
50W
Power Consumption (Stand-by)
<0.5W
Amplifier
Amplifier Typ.
2.1 CH
Rated Output Power (Sound Bar)
120W, 30W x 4, Test Mode@THD=10%
Rated Output Power (Subwoofer)
200W, Test Mode@THD=10%
Rated Output Power (Total)
320W
Amplifier IC Model (Sound Bar (FR / FL /) (Full Range Amp)
STA369BW
Amplifier IC Model (Sound Bar (FR / FL /) (Tweeter Amp)
STA369BW
Amplifier IC Model (Subwoofer)
STA510F
Speaker
SoundBar Speaker (FL / FR)
(1 Full Range + 1 Tweeter) x 2, Total 4 Speakers
SoundBar Speaker (FL / FR) (Full Range)
40 x 100mm 2pcs
SoundBar Speaker (FL / FR) (Tweeter)
1.5 inch 2pcs
SubWoofer Speaker
Woofers + Port
SubWoofer Speaker
8" Woofer, 4 ohm
Decoder
Dolby Digital
√
PCM
√
MultichPCM
√
Others
WAV / WMA / MP3 / FLAC
Sound Enhancement

Surround Virtualizer
√
Sound Mode
Movie
Sound Mode
Music
Sound Mode
News
Function Features
Wireless Subwoofer
BT
HDMI OUT (ARC)
√
Bluetooth Audio
√
BT Version
BT 4.1
OPTICAL INPUT
√
COAXIAL INPUT
√
Aux INPUT
3.5mm Phone Jack
Auto Wake Mode (Enter Mode Method)
“Source”& “Vol+” (On Soundbar)
Auto Wake Mode (Support Input)
AUX / Coaxial / Optical / ARC (Not for BT / USB)
Auto Power Off
√
Wall Mountable
√
USB Audio (Type A)
Support, 1 port
USB port for Service (FW update)
Share USB Type A
Compatible with TV Remote Control Code
TV: Vol+, Vol-, Mute
Shop mode
“Source”& “Vol-” (On Soundbar)
Display / Indicator
Soundbar (Main Display)
5 LED display in white colour
Soundbar
Standby LED
Subwoofer (Standby LED)
Blue LED
Control Keys (On Main Unit)
On Sound Bar (Front Panel)
On / Standby

On Sound Bar (Front Panel)
Input / Source
On Sound Bar (Front Panel)
Volume +
On Sound Bar (Front Panel)
Volume –
ON Subwoofer (Rear Panel)
ID Set
Terminals
Soundbar
HDMI Output (ARC)
Soundbar
Optical input
Soundbar
Coaxial input
Soundbar
AUX In (3.5mm)
Soundbar – USB (Type A)
1, USB Audio and FW update
Soundbar
Power Supply Socket (AC)
Subwoofer
Power Supply Socket (AC)
Key Components
DSP
SPHE8107S-A
Bluetooth IC / Module
RDA5876
Wireless to Subwoofer
Bluetooth
Remote Control
Type
IR
Battery
AAA Battery
Control Keys
On / Standby (SB)
Control Keys
SOURCE
Control Keys
Volume +
Control Keys
Volume –
Control Keys
Next [Navigation / BT / USB]
Control Keys
Previous [Navigation / BT / USB]
Control Keys
Play / Pause / Paring [BT / USB]

Control Keys
EQ
Control Keys
BASS+
Control Keys
BASS-
Control Keys
Mute
Control Keys
BT
Control Keys (Total Key Qty.)
13
What' In Box
Main Unit (Soundbar)
1 PCS
Subwoofer
1 PCS
Remote Control
1 PCS
Battery for Remote Control
AAA Battery x 2
3.5mm audio cable
0 PCS
Optical Cable
1 PCS
Coaxial Cable
0
AC power cord
2 PCS
Operation Manual
1 PCS
Quick Guide
1 PCS
Wall Mount Angle
1 Set
Wall Mount Guide
1 PCS
Shipping Details
Sound Bar (Net weight (kg))
1.9
Sound Bar (Dimensions (WxHxD) mm)
998x60x93
Subwoofer (Net weight (kg))
6.3
Subwoofer (Dimensions (WxHxD) mm)
245x360x312
Total System (Gross weight (kg))
10.5
Total System (Dimensions (WxHxD) mm)
1058x498x331